

THE ORIGINAL SINCE 1967

cry baby
KIRK HAMMETT

LIVE TO PLAY LIVE®



JIMDUNLOP.COM

92503008027revD

KH95 KIRK HAMMETT CRY BABY® WAH WAH

POWER

The Kirk Hammett Signature Cry Baby® Wah Wah is powered by one 9-volt battery (accessed via the bottom of the pedal), an AC adapter such as the Dunlop ECB003/ ECB003E, or a DC Brick™ power supply.

SETUP INSTRUCTIONS

- Run a shielded instrument cable from your guitar to the KH95's INSTRUMENT jack.
- Run another shielded instrument cable from the KH95's AMPLIFIER jack into your amplifier input.
- Turn on the amplifier and begin playing.
- To turn the pedal on/off, push the toe of the pedal down until you feel a "click".
- By rocking your foot back and forth on the pedal, you can change the effect that the Cry Baby has on the tone of your instrument instantaneously.

SPECIFICATIONS

Impedance

Input	680 kΩ
Output	4.7 kΩ

Filter Parameter

Low Pass	300 Hz to 380 Hz
High Pass	1.4 kHz to 1.8 kHz

Maximum Level

Input	-13.5 dBV
Output	+6.5 dBV

Maximum Gain

Heel Down	+17 dB at 300 Hz to 380 Hz
Toe Down	+21 dB at 1.4 kHz to 1.8 kHz

Noise Floor*

Heel Down	>95 dBV
Toe Down	>89 dBV

Bypass	Hardwire
---------------	----------

Current Draw	4 mA
---------------------	------

Power Supply	9 volts DC
---------------------	------------

*OdBV=1V_{RMS}, A-weighted

